

# HPE Networking Legacy Product Family 10-GbE Transceiver Support Matrix

		Genuine HPE SFP+ Transceivers and Cables						
HPE Networking Switch Series	Product Name	Product Number	10GBASE-SR, LR, LRM	10GBASE-ER	10-GbE SFP+ Direct Attach Cables		10-GbE XFP-SFP+ Direct Attach Cables	
			(J9150A, J9151A, J9152A)	(J9153A)	1m, 3m, 7m (J9281A, J9283A, J9285A)	10m, 15m* (J9286B, J9287B)	1m, 3m, 5m (J9300A, J9301A, J9302A)	
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	
2530	2530-24G-2SFP+ Switch 2530-48G-2SFP+ Switch 2530-24G-PoE+-2SFP+ Switch 2530-48G-PoE+-2SFP+ Switch	J9856A J9855A J9854A J9853A	all software versions	all software versions	all software versions	all software versions	all software versions	all software versions
2910al	2910al-24G Switch 2910al-48G Switch 2910al-24G-PoE+ Switch 2910al-48G-PoE+ Switch 2-Port 10-GbE SFP+ al Module	J9145A J9147A J9146A J9148A J9008A	-- -- -- -- all software versions	-- -- -- -- W.15.07.0002 and later	-- -- -- -- all software versions	-- -- -- -- W.14.28 and later	-- -- -- -- W.15.07.0002 and later	-- -- -- -- W.14.28 and later
2920	2920-24G Switch 2920-48G Switch 2920-24G-PoE+ Switch 2920-48G-PoE+ Switch 2920-48G-POE+ 740W Switch	J9726A J9728A J9727A J9729A J9836A	-- -- -- -- --	-- -- -- -- --	-- -- -- -- --	-- -- -- -- --	-- -- -- -- --	-- -- -- -- --
2930F	2930F 24G 4SFP+ Switch 2930F 48G 4SFP+ Switch 2930F 24G PoE+ 4SFP+ Switch 2930F 48G PoE+ 4SFP+ Switch 2930F 8G PoE+ 2SFP+ Switch 2930F 24G PoE+ 4SFP+ TAA Switch 2930F 48G PoE+ 4SFP+ TAA Switch 2930F 24G 4SFP Switch 2930F 48G 4SFP Switch 2930F 24G PoE+ 4SFP Switch 2930F 48G PoE+ 4SFP Switch	JL253A JL254A JL255A JL256A JL258A JL263A JL264A JL259A JL260A JL261A JL262A	all software versions (J9150A and J9151A only)	all software versions	-- -- -- -- -- -- -- -- -- -- -- --	all software versions (J9281B and J9283B only)  J9285B (7m) not supported	-- -- -- -- -- -- -- -- -- -- -- --	all software versions  all software versions
3500yl	Switch 3500yl-24G-PWR Switch 3500yl-48G-PWR 3500yl-24G-PoE+ Switch 3500yl-48G-PoE+ Switch 10-GbE 2-Port SFP+ / 2-Port CX4 yl Module	J8692A J8693A J9310A J9311A J9312A	-- -- -- -- K.14.50 and later	-- -- -- -- K.15.02.0004 and later	-- -- -- -- K.14.50 and later	-- -- -- -- K.14.50 and later	-- -- -- -- K.15.05.0001 and later	-- -- -- -- K.14.50 and later

\* These direct attach cables are no longer available for sale.

## HPE Networking Legacy Product Family 10-GbE Transceiver Support Matrix (cont'd)

		Genuine HPE SFP+ Transceivers and Cables						
HPE Networking Switch Series	Product Name	Product Number	10GBASE-SR, LR, LRM	10GBASE-ER	10-GbE SFP+ Direct Attach Cables		10-GbE XFP-SFP+ Direct Attach Cables	
			(J9150A, J9151A, J9152A)	(J9153A)	1m, 3m, 7m (J9281A, J9283A, J9285A)	10m, 15m (J9281B, J9283B, J9285B)	10m, 15m (J9286B, J9287B)	1m, 3m, 5m (J9300A, J9301A, J9302A)
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software
3800	3800-24G-2SFP+ Switch	J9575A	all software versions	all software versions	all software versions	all software versions	KA.15.09.0003 and later	all software versions
	3800-48G-4SFP+ Switch	J9576A						
	3800-24G-PoE+-2SFP+ Switch	J9573A						
	3800-48G-PoE+-4SFP+ Switch	J9574A						
	3800-24SFP-2SFP+ Switch	J9584A						
3810M	3810M 24G 1-slot Switch	JL071A*	all software versions	all software versions	all software versions	all software versions	all software versions	all software versions
	3810M 48G 1-slot Switch	JL072A*						
	3810M 24G PoE+ 1-slot Switch	JL073A*						
	3810M 48G PoE+ 1-slot Switch	JL074A*						
	3810M 16SFP+ 2-slot Switch	JL075A						
	3810M 40G HPE Smart Rate PoE+ 1-slot Switch	JL076A*						
	*For use in the <b>JL075A</b> 3810M switch or in any 3810M switch with a <b>JL083A</b> Aruba 3810M 4SFP+ Module installed.							
5400zl	4-Port 10-GbE SFP+ zl Module	J9309A	K.14.39 and later	K.15.02.0004 and later	K.14.39 and later	K.14.39 and later	K.15.05.0001 and later	K.14.39 and later
	8-Port 10-GbE SFP+ v2 zl Module	J9538A	K.15.02.0004 and later	K.15.02.0004 and later	K.15.02.0004 and later	K.15.02.0004 and later	K.15.05.0001 and later	K.15.02.0004 and later
	20-Port Gig-T / 2-Port SFP+ v2 zl Module	J9548A						
	20-Port Gig-T PoE+ / 2-Port SFP+ v2 zl Module	J9536A						

## HPE Networking Legacy Product Family 10-GbE Transceiver Support Matrix (cont'd)

HPE Networking Switch Series	Product Name	Product Number	Genuine HPE SFP+ Transceivers and Cables					
			10GBASE-SR, LR, LRM (J9150A, J9151A, J9152A)	10GBASE-ER (J9153A)	10-GbE SFP+ Direct Attach Cables		10-GbE XFP-SFP+ Direct Attach Cables 1m, 3m, 5m (J9300A, J9301A, J9302A)	
			Supported with This Software	Supported with This Software	1m, 3m, 7m (J9281A, J9283A, J9285A)	10m, 15m (J9281B, J9283B, J9285B)	10m, 15m (J9286B, J9287B)	Supported with This Software
5400R	8-Port 10-GbE SFP+ v2 zl Module	J9538A	all software versions	all software versions	all software versions	all software versions	all software versions	all software versions
	20-Port Gig-T / 2-Port SFP+ v2 zl Module	J9548A						
	20-Port Gig-T PoE+ / 2-Port SFP+ v2 zl Module	J9536A						
	20p PoE+ /4p SFP+ v3 zl2 Module	J9990A	KB.15.17 and later	KB.15.17 and later	(not supported)	KB.15.17 and later	KB.15.17 and later	KB.15.17 and later
	8p 1G/10GbE SFP+ v3 zl2 Module	J9993A	KB.15.17 and later	KB.15.17 and later	(not supported)	KB.15.17 and later	KB.15.17 and later	KB.15.17 and later
6120	6120G/XG Blade Switch	498358-B21	--	--	--	--	--	all software versions
	6120XG Blade Switch	516733-B21	all software versions	(not supported)	all software versions	all software versions	Z.14.28 and later	
6200yl	Switch 6200yl-24G-mGBIC	J8992A	--	--	--	--	--	--
	10-GbE 2-Port SFP+ / 2-Port CX4 yl Module	J9312A	K.14.50 and later	K.15.02.0004 and later	K.14.50 and later	K.14.50 and later	K.15.05.0001 and later	K.14.50 and later
6600	6600-24G-4XG Switch	J9264A	K.14.03 and later	K.15.02.0004 and later	K.14.03 and later	K.14.32 and later	K.15.05.0001 and later	K.14.32 and later
	6600-24XG Switch	J9265A						
	6600-48G-4XG Switch	J9452A						
8200zl	4-Port 10-GbE SFP+ zl Module	J9309A	K.14.39 and later	K.15.02.0004 and later	K.14.39 and later	K.14.39 and later	K.15.05.0001 and later	K.14.39 and later
	8-Port 10-GbE SFP+ v2 zl Module	J9538A	K.15.02.0004 and later	K.15.02.0004 and later	K.15.02.0004 and later	K.15.02.0004 and later	K.15.05.0001 and later	K.15.02.0004 and later
	20-Port Gig-T / 2-Port SFP+ v2 zl Module	J9548A						
	20-Port Gig-T PoE+ / 2-Port SFP+ v2 zl Module	J9536A						

## HPE Networking Legacy Product Family 10-GbE Transceiver Support Matrix (cont'd)

HPE Networking Switch Series	Product Name	Product Number	Genuine HPE X2 Transceivers					Genuine HPE Optical Media Converter (OMC) for CX4 <sup>1</sup> (J8439A)
			10GBASE-SR, LR (J8436A, J8437A)	10GBASE-LRM (J9144A)	10GBASE-ER (J8438A)	10GBASE-CX4 (J8440A)   (J8440B/C)		
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software
2900	Switch 2900-24G Switch 2900-48G	J9049A J9050A	all software versions	T.13.18 and later	all software versions	all software versions	all software versions	all software versions, OMC for fixed CX4 ports only
2910al	2910al-24G Switch 2910al-48G Switch 2910al-24G-PoE+ Switch 2910al-48G-PoE+ Switch 2-Port 10-GbE CX4 al Module	J9145A J9147A J9146A J9148A J9149A	-- -- -- -- --	-- -- -- -- --	-- -- -- -- --	-- -- -- -- --	-- -- -- -- --	-- -- -- -- all software versions
2930F	2930F 24G 4SFP+ Switch 2930F 48G 4SFP+ Switch 2930F 24G PoE+ 4SFP+ Switch 2930F 48G PoE+ 4SFP+ Switch 2930F 8G PoE+ 2SFP+ Switch 2930F 24G PoE+ 4SFP+ TAA Switch 2930F 48G PoE+ 4SFP+ TAA Switch 2930F 24G 4SFP Switch 2930F 48G 4SFP Switch 2930F 24G PoE+ 4SFP Switch 2930F 48G PoE+ 4SFP Switch	JL253A JL254A JL255A JL256A JL258A JL263A JL264A JL259A JL260A JL261A JL262A	-- -- -- -- -- -- -- -- -- -- --	-- -- -- -- -- -- -- -- -- -- --	-- -- -- -- -- -- -- -- -- -- --	-- -- -- -- -- -- -- -- -- -- --	-- -- -- -- -- -- -- -- -- -- --	-- -- -- -- -- -- -- -- -- -- --
3400cl	Switch 3400cl-24G Switch 3400cl-48G Switch cl 10-GbE CX4 Copper Module Switch cl 10-GbE Media Flex Module	J4905A J4906A J8434A J8435A	-- -- -- M.08.54 and later	-- -- -- (not supported)	-- -- -- M.08.75 and later	-- -- -- M.08.54 and later	-- -- -- M.10.06 and later	-- -- M.08.54 and later, OMC for J8434A & J8440A/B
3500yl	Switch 3500yl-24G-PWR Switch 3500yl-48G-PWR 3500yl-24G-PoE+ Switch 3500yl-48G-PoE+ Switch Switch yl 10-GbE 2-Port CX4 + 2-Port X2 Module 10-GbE 2-Port SFP+ / 2-Port CX4 yl Module	J8692A J8693A J9310A J9311A J8694A J9312A	-- -- -- -- all software versions --	-- -- -- -- K.13.20 and later --	-- -- -- -- all software versions --	-- -- -- -- all software versions --	-- -- -- -- K.11.17 and later --	-- -- -- -- all software versions, OMC for fixed CX4 ports only K.14.50 and later

## HPE Networking Legacy Product Family 10-GbE Transceiver Support Matrix (cont'd)

HPE Networking Switch Series	Product Name	Product Number	Genuine HPE X2 Transceivers					Genuine HPE Optical Media Converter (OMC) for CX4 <sup>1</sup> (J8439A)
			10GBASE-SR, LR (J8436A, J8437A)	10GBASE-LRM (J9144A)	10GBASE-ER (J8438A)	10GBASE-CX4 (J8440A)   (J8440B/C)		
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software
3810M	3810M 24G 1-slot Switch	JL071A*						
	3810M 48G 1-slot Switch	JL072A*						
	3810M 24G PoE+ 1-slot Switch	JL073A*	(not supported)	(not supported)	(not supported)	(not supported)	(not supported)	(not supported)
	3810M 48G PoE+ 1-slot Switch	JL074A*						
	3810M 16SFP+ 2-slot Switch	JL075A						
	3810M 40G HPE Smart Rate PoE+ 1- *For use in the <b>JL075A</b> 3810M switch or in any 3810M switch with a <b>JL083A</b> Aruba 3810M 4SFP+ Module installed.	JL076A*						
4200vl	Switch vl 1-Port 10-GbE X2 Module	J8766A	L.11.08 and later	L.11.11 and later	L.11.08 and later	L.11.08 and later	L.11.08 and later	L.11.08 and later
5300xl	Switch xl 1-Port 10-GbE X2 Module	J8988A	E.11.02 and later	(not supported)	E.11.02 and later	E.11.02 and later	E.11.02 and later	E.11.02 and later
5400zl	Switch zl 4-Port 10-GbE X2 Module	J8707A	all software versions	K.13.20 and later	all software versions	all software versions	K.11.17 and later	K.11.33 and later, OMC for J8708A & J8440A/B
	Switch zl 4-Port 10-GbE CX4 Module	J8708A	--	--	--	--	--	
5400R	20p PoE+/4p SFP+ v3 zl2 Module	J9990A	--	--	--	--	--	--
	8p 1G/10GbE SFP+ v3 zl2 Module	J9993A	--	--	--	--	--	--
6200yl	Switch 6200yl-24G-mGBIC	J8992A	--	--	--	--	--	--
	Switch yl 10-GbE 2-Port CX4 + 2-Port X2 Module	J8694A	K.11.33 and later	K.13.20 and later	K.11.33 and later	K.11.33 and later	K.11.33 and later	K.11.33 and later, OMC for fixed CX4 ports only
	10-GbE 2-Port SFP+ / 2-Port CX4 yl Module	J9312A	--	--	--	--	--	K.14.50 and later
6400cl	Switch 6400cl (CX4)	J8433A	--	--	--	--	--	M.08.62 and later, OMC for J8433A & J8440A/B
	Switch 6410cl (X2)	J8474A	M.08.62 and later	(not supported)	M.08.75 and later	M.08.62 and later	M.08.102 and later	
	Switch cl 10-GbE CX4 Copper Module	J8434A	--	--	--	--	--	M.08.62 and later, OMC for J8434A & J8440A/B
	Switch cl 10-GbE Media Flex Module	J8435A	M.08.62 and later	(not supported)	M.08.75 and later	M.08.62 and later	M.08.102 and later	
8100fl	Switch fl 1-Port 10-GbE X2 Interface Module	J8736A	CY.02.03.0005 and later	(not supported)	CY.02.03.0005 and later	CY.02.03.0005 and later	CY.02.03.0005 and later	CY.02.03.0005 and later, OMC for J8440A/B
	Switch fl 2-Port 10-GbE X2 Interface Module	J8737A	CY.02.05.0001 and later	(not supported)	CY.02.05.0001 and later	CY.02.05.0001 and later	CY.02.05.0001 and later	CY.02.05.0001 and later, OMC for J8440A/B
8200zl	Switch zl 4-Port 10-GbE X2 Module	J8707A	all software versions	K.13.20 and later	all software versions	all software versions	all software versions	all software versions, OMC for J8708A & J8440A/B
	Switch zl 4-Port 10-GbE CX4 Module	J8708A	--	--	--	--	--	

			<b>Genuine HPE XENPAK Transceivers</b>
			<b>10GBASE-SR, LR, ER</b> (J8175A, J8173A, J8176A)
<b>HPE Networking Switch Series</b>	<b>Product Name</b>	<b>Product Number</b>	<b>Supported with This Software</b>
9300m	9300 2-Port 10-GbE Module	J8174A	07.6.04 and later
9408sl	9400sl 4-Port 10-GbE Module	J8682A	all software versions

Footnotes

<sup>1</sup> The J8439A Optical Media Converter is supported in the J8440A and J8440B CX4 transceivers, but not in the J8440C.

© Copyright 2014-2016 Hewlett Packard Enterprise Development LP  
The information contained herein is subject to change without notice.

May 2016  
5200-1981

