

Enters Router PIM context.

Configures and automatically enables C-BSR operation for all possible groups (224.0.0.0/4).

Removes support for the default group entry for all possible groups (224.0.0.0/4).

Configures static-RP support with override.

```
HP Switch(config)# router pim
HP Switch(pim)# bsr-candidate source-ip-vlan 120
HP Switch(pim)# rp-candidate source-ip-vlan 120
HP Switch(pim)# rp-candidate group-prefix 231.128.64.0/18
HP Switch(pim)# rp-candidate group-prefix 230.255.1.1/32
HP Switch(pim)# no rp-candidate group-prefix 224.0.0.0/4
HP Switch(pim)# rp-address 120.11.10.1 231.128.64.0/18
override
HP Switch(pim) #
```

Note: The static RP takes precedence over the C-RP for multicast groups in the range of 231.128.64.0/18 because the mask configured for the static RP meets the criteria of being either equal to or greater than the mask configured for the same group in the C-RP. For example, if the mask for the static-RP was 17 or less, the override would not take effect (even though configured), and the C-RP configuration would take precedence.